



IPC-HERMES-9852
Version 1.4



IPC-HERMES-9852

The Global Standard for Machine-to-Machine Communication in SMT Assembly

Developed by The Hermes Standard initiative and approved by IPC

Supersedes:

IPC-HERMES-9852, Version 1.3 –
May 2021

IPC-HERMES-9852, Version 1.2 –
June 2019

Users of this publication are encouraged to participate in the development of future revisions.

Contact:

IPC

Tel 847 615.7100
Fax 847 615.7105

Figure 7	Communication Sequence in Scenario U1a	7	Figure 20	Connection, Handshake and Connection Loss Detection on Vertical Channel	19
Figure 8	Communication Sequence in Scenario U1b	8	Figure 21	Example for Connection Loss Detection With Featurecheckaliveresponse on Vertical Channel	20
Figure 9	Communication sequence in Scenario U2	9	Figure 22	Hermes Interface States on Vertical Channel	21
Figure 10	Communication Sequence in Scenario U3	10	Figure 23	Explanation for Top and Bottom Clearance Height	26
Figure 11	Communication Sequence in Scenario D1	11	Figure 24	Line Setup With Barcode Readers and Repair Station	43
Figure 12	Communication Sequence in Scenario D2	12	Figure 25	Line Setup With Fixed and Mobile Barcode Readers	
Figure 13	Communication Sequence in Scenario D3	13	Figure 26	SMT Subline That Is Involved in Oven Error Loop	45
Figure 14	Example of Communication Sequence for BoardForecast	14	Figure 27	Example Subline Showing Use Case Request Pause / Confirm Pause and Resume Operation	46
Figure 15	Example of Communication Sequence for Boardforecast With RevokeMachineReady	14	Figure 28	Board Removal at Downstream Conveyor	47
Figure 16	Example of Communication Sequence With Several BoardForecast	15	Figure 29	Reversal Transportation, Downstream Flipping Unit	47
Figure 17	Example of Communication Sequence in Case With Error Handling	16	Figure 30	Reversal Transportation, Upstream Flipping Unit	48
Figure 18	Example of Communication Sequence BoardForecast Without Product Change	16	Figure 31	Board Routing, Predefined Routes	49
Figure 19	Hermes Interface States on Horizontal Channel	17	Figure 32	Board Routing, Multiple Target Locations	50

The Global Standard for Machine-to-Machine Communication in SMT Assembly

1 SCOPE

The aim of this specification is to create a state-of-the-art communication protocol for surface-mount technology (SMT) production lines. Therefore, this new communication protocol has to cope with the following:

- Replace the electrical SMEMA interface as specified in IPC-SMEMA-9851
- Extend the interface to communicate:
 - Unique identifiers for the handled printed circuit boards (PCBs)
 - Equipment identifiers of the first machine noticing a PCB
 - Barcodes
 - Conveyor speed
 - Product type specific information:
 - Product type identifier
 - Length
 - Width
 - Thickness
 - ...

With respect to version numbers The Hermes Standard adheres to the rules of Semantic Versioning 2.0.0 [SemVer_2.0.0].

Hints on naming:

- Wherever a feature is described by the word “shall“ it is mandatory.
- The word “machine” is used for any equipment which can be found in a SMT production line (e.g., printers, placement machines, ovens, AOIs, transport modules, shuttles, stackers).
- The term “PCB” may also refer to carriers transporting PCBs.
- The word “Hermes” is used as abbreviation for “The Hermes Standard”.
- “The Hermes Standard” and IPC-HERMES-9852 are synonyms for the standard specified in this document and might be used interchangeably.

2 TECHNICAL CONCEPT

2.1 Prerequisites This specification is based on the prerequisite, that any application implementing this protocol has to provide connectivity based on Internet Protocol (IP) [IETF_RFC_791] / [IETF_RFC_2460] via Transmission Control Protocol (TCP) [IETF_RFC_793] (ISO / OSI model [ISO_7498-1] layer 3) to the adjacent machines and for communication with supervisory systems.

2.2 Board IDs Board individuals are identified by board IDs. These must be Globally Unique Identifiers (GUIDs) according to [ITU-T_REC_X.667], e.g., 123e4567-e89b-12d3-a456-426655440000. They are generated by the first machine in a consecutive row of machines implementing the Hermes protocol. The board ID is passed from machine to machine. If a machine in a line does not implement the Hermes protocol, the board ID is lost and a new one will be generated by the next machine implementing Hermes.




Figure 1 Generation of Board IDs